

# SA Compatibility List



| MFG              | Model                                    | RU | Depth  | Switch Intake | Switch Exhaust | Passive Recommended Best Fit | Active Recommended Best Fit |
|------------------|--|----|--------|---------------|----------------|------------------------------|-----------------------------|
| ACS              | 48 Cyclade                               | 1  |        | side          | side           | SA1-01001NB                  | SA2-003                     |
| Alcatel          | 6850 Omniswitch                          | 1  |        | side          | side           | SA1-01001NB                  | SA2-003                     |
| Alcatel          | 6900 Omniswitch                          | 1  |        | front         | rear           | n/a                          | SA2-004                     |
| Alied Telesys    | AT9924T                                  | 1  | 16.7"  | front         | rear           | n/a                          | SA2-004                     |
| Arista           | 7010T                                    | 1  | 10"    | front<br>rear | rear<br>front  | n/a<br>SA1-01002XLNB         | SA2-004<br>SA2-002          |
| Arista           | 7048-A                                   | 1  | 16"    | front<br>rear | rear<br>front  | n/a<br>SA1-01002L            | SA2-004<br>SA2-002          |
| Arista           | 7048T                                    | 1  | 16"    | front<br>rear | rear<br>front  | n/a<br>SA1-01002L            | SA2-004<br>SA2-002          |
| Arista           | 7050SX                                   | 2  | 18.1"  | front<br>rear | rear<br>front  | n/a<br>SA1-02003             | n/a<br>SA2-002              |
| Arista           | 7050T                                    | 1  | 16"    | front<br>rear | rear<br>front  | n/a<br>SA1-01002L            | SA2-004<br>SA2-002          |
| Arista           | 7148SX                                   | 1  | 16"    | front<br>rear | rear<br>front  | n/a<br>SA1-01002L            | SA2-004<br>SA2-002          |
| Arista           | 7150                                     | 1  | 16"    | front<br>rear | rear<br>front  | n/a<br>SA1-01002L            | SA2-004<br>SA2-002          |
| Arista           | 7280                                     | 1  | 20.6"  | front<br>rear | rear<br>front  | n/a<br>SA1-01002             | SA2-004<br>SA2-002          |
| Aruba            | 3400                                     | 1  |        | side          | side           | SA1-01001NB                  | SA2-003                     |
| Blade Rackswitch | G8052                                    | 1  | 17.5"  | front<br>rear | rear<br>front  | n/a<br>SA1-01002L            | SA2-004<br>SA2-002          |
| Brocade          | 300, 300a                                | 1  | 12.07" | rear          | front          | SA1-01002XLNB                | SA2-002                     |
| Brocade FCX      | 624, 648                                 | 1  |        | front         | rear           |                              | SA2-004                     |
| Brocade FCX      | 624, 648                                 | 1  |        | rear          | front          | SA1-01002                    | SA2-002                     |
| Brocade FCX      | 624-E, 648-E                             | 1  |        | front         | rear           |                              | SA2-004                     |
| Brocade FCX      | 624-I, 648-I                             | 1  |        | rear          | front          | SA1-01002                    | SA2-002                     |
| Brocade FCX      | 624S, 624S-F, 648S, 624S-HPOE, 648S-HPOE | 1  |        | front/ side   | rear           | SA1-01001NB                  | SA2-002                     |
| Brocade NI-CER   | 202C-AC                                  | 1  |        | front         | rear           | n/a                          | SA2-004                     |
| Brocade VDX      | 6740                                     | 1  | 16.25" | front<br>rear | rear<br>front  | n/a<br>SA1-01002LNB          | SA2-004<br>SA2-002          |
| Brocade VDX      | 6740T                                    | 1  | 21.12" | front<br>rear | rear<br>front  | n/a<br>SA1-01002             | SA2-004<br>SA2-002          |
| Brocade VDX      | 6740T-1G                                 | 1  | 21.12" | front<br>rear | rear<br>front  | n/a<br>SA1-01002             | SA2-004<br>SA2-002          |
| Brocade VDX      | 6940-36Q                                 | 1  | 16.25" | rear          | front          | SA1-01002LNB                 | SA2-002                     |
| Brocade VDX      | 6940-36Q                                 | 1  | 16.25" | front         | rear           | n/a                          | SA2-004                     |
| Brocade VDX      | 6940-144S                                | 2  | 18"    | rear          | front          | n/a                          | SA2-002                     |
| Brocade VDX      | 6940-144S                                | 2  | 18"    | front         | rear           | n/a                          | SA2-004                     |
| Cisco            | 903                                      | 3  | 9.22"  | side          | side           | SA1-03001                    | n/a                         |
| Cisco            | 2232 series                              | 1  |        | rear          | front          | SA1-01002                    | SA2-002                     |
| Cisco            | 2248                                     | 1  | 17.7"  | rear          | front          | SA1-01002L                   | SA2-002                     |
| Cisco            | 2821                                     | 1  |        | side          | side           | SA1-01001NB                  | SA2-003                     |
| Cisco            | 2851                                     | 2  |        | side          | side           | SA1-02005                    | SA2-003                     |
| Cisco            | 2901                                     | 1  | 17.3"  | front         | side           | n/a                          | SA2-004                     |
| Cisco            | 2911                                     | 2  | 12"    | side          | side           | SA1-02005                    | SA2-003                     |
| Cisco            | 2921                                     | 2  | 15.5"  | rear/side     | front          | n/a                          | SA2-002                     |
| Cisco            | 2950                                     | 1  |        | side          | rear           | SA1-01001NB                  | SA2-002                     |
| Cisco            | 2951                                     | 2  | 18.5"  | rear/side     | front          | n/a                          | SA2-002                     |
| Cisco            | 2960                                     | 1  |        | side          | rear           | SA1-01001NB                  | SA2-002                     |
| Cisco            | 2960G                                    | 1  | 12.9"  | front<br>rear | rear<br>front  | n/a<br>SA1-01002XLNB         | SA2-004<br>SA2-002          |
| Cisco            | 2960S                                    | 1  |        | side          | rear           | SA1-01001NB                  | SA2-002                     |
| Cisco            | 2960-24-S                                | 1  | 9.3"   | sides         | rear           | SA1-01001NB                  | SA2-002                     |
| Cisco            | 2960-24LC-S                              | 1  | 13"    | sides         | rear           | SA1-01001NB                  | SA2-002                     |
| Cisco            | 3064 ask cust airflow                    | 1  |        | rear          | front          | SA1-01002                    | SA2-002                     |

|            |                          |    |            |             |            |                |                 |
|------------|--------------------------|----|------------|-------------|------------|----------------|-----------------|
| Cisco      | 3064 ask cust airflow    | 1  |            | front       | rear       | n/a            | SA2-004         |
| Cisco      | 3524                     | 1  | 18.38"     | rear        | front      | SA1-01002      | SA2-002         |
| Cisco      | 3524                     | 1  | 18.38"     | front       | rear       | n/a            | SA2-004         |
| Cisco      | 3548                     | 1  | 18.38"     | rear        | front      | SA1-01002      | SA2-002         |
| Cisco      | 3548                     | 1  | 18.38"     | front       | rear       | n/a            | SA2-004         |
| Cisco      | 3550 24 & 48             | 1  |            | side        | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 3550-24                  | 1  |            | side        | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 3550-48                  | 1  |            | side        | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 3560-24                  | 1  |            | side        | side       | n/a            | SA2-003         |
| Cisco      | 3560-48 series           | 1  |            | side        | side       | n/a            | SA2-003         |
| Cisco      | 3560G-24                 | 1  |            | side        | side       | n/a            | SA2-003         |
| Cisco      | 3560G-48 series          | 1  |            | side        | side       | n/a            | SA2-003         |
| Cisco      | 3560x                    | 1  | 18-19.5"   | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3650-24T                 | 1  | 17.625"    | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3650-24P                 | 1  | 17.625"    | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3650-48T                 | 1  | 17.625"    | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3650-48P                 | 1  | 17.625"    | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3650-48F                 | 1  | 19.125"    | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3750                     | 1  |            | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3750E-12D                | 1  |            | front       | rear       | n/a            | SA2-004         |
| Cisco      | 3750E-12SD               | 1  |            | front /side | rear       | n/a            | SA2-004         |
| Cisco      | 3750E-24 & 48 port       | 1  |            | side        | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 3750G-24 & 48TS          | 2  |            | side        | side       | SA1-01001NB    | SA2-003         |
| Cisco      | 3750X                    | 1  | 17.5"      | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3750-24P                 | 1  | 17.5"      | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3750-48P                 | 1  | 17.5"      | front/ side | rear       | n/a            | SA2-004         |
| Cisco      | 3850                     | 1  | 17.5-19.2" | front rear  | rear front | n/a SA1-01002  | SA2-004 SA2-002 |
| Cisco WS-C | 3850-48F-L               | 1  | 19.2"      | front       | rear       | n/a            | SA2-004         |
| Cisco      | 4200                     | 1  |            | sides       | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 4400 (AIR-WLC4402-25-K9) | 1  |            | right side  | left side  | SA1-01001NB    | SA2-003         |
| Cisco      | EX4550                   | 1  |            | front rear  | front      | n/a n/a        | n/a SA2-004     |
| Cisco      | 4900M                    | 2  |            | side        | side       | n/a            | SA2-003         |
| Cisco      | 4924                     | 1  | 16"        | sides       | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 4928 series              | 1  | 16.1"      | side        | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 4948                     | 1  | 16.14"     | sides       | rear       | SA1-01001NB    | SA2-002         |
| Cisco      | 4948-S                   | 1  |            | sides       | rear       | SA1-01001NB    | SA2-004         |
| Cisco      | 4948E                    | 1  |            | front       | rear       | n/a            | SA2-004         |
| Cisco      | 4948E-BDL                | 1  |            | front       | rear       | n/a            | SA2-004         |
| Cisco      | 4948E-E                  | 1  |            | front       | rear       | n/a            | SA2-004         |
| Cisco WS-C | 4948E-F                  | 1  | 19.4"      | rear        | front      | SA1-01002      | SA2-002         |
| Cisco      | 4948E-F_BDL              | 1  |            | rear        | front      | SA1-01002      | SA2-002         |
| Cisco      | 4948E-F-E                | 1  |            | rear        | front      | SA1-01002      | SA2-002         |
| Cisco      | 4948E-F-S                | 1  |            | rear        | front      | SA1-01002      | SA2-002         |
| Cisco      | 4948E-S                  | 1  |            | front       | rear       | n/a            | SA2-004         |
| Cisco      | 4980                     | 1  |            | front rear  | rear front | n/a SA1-01002L | SA2-004 SA2-002 |
| Cisco      | 6503 6503E               | 4  |            | side        | side       | n/a            | SA2-006         |
| Cisco      | 6504-E                   | 5  |            | side        | side       | n/a            | SA2-006         |
| Cisco      | 6506-E                   | 12 |            | side        | side       | SA1-09001      | SA2-006         |
| Cisco      | 6509 (open post only)    | 15 |            | side        | side       | SA1-09001      | SA2-006         |
| Cisco      | 6509E                    | 15 |            | r side      | l side     | SA1-09001      | SA2-006         |
| Cisco      | 6509-NEB                 | 20 |            | front       | rear       | n/a            | SA2-006         |
| Cisco      | 6509-NEB-A               | 21 |            | front       | rear       | n/a            | SA2-006         |
| Cisco      | 6509-V-E                 | 21 |            | front       | rear       | n/a            | SA2-006         |
| Cisco      | 6513E                    | 19 |            | r side      | l side     | n/a            | SA2-006         |
| Cisco      | 6807-XL                  | 10 | 18"        | r side      | l side     | SA1-09001      | SA2-006         |
| Cisco      | 6880-X                   | 5  | 23"        | r side      | l side     | SA1-09001      | SA2-006         |
| Cisco      | 7009 (open post only)    | 14 |            | side        | side       | SA1-11001      | SA2-006         |
| Cisco      | 7018 (open post only)    | 25 |            | side        | side       | SA1-09001 X2   | n/a             |

|                  |                  |    |        |               |               |                    |                    |
|------------------|------------------|----|--------|---------------|---------------|--------------------|--------------------|
| Cisco            | 9336PQ           | 2  | 22.5"  | front<br>rear | rear<br>front | n/a<br>SA1-02003 S | n/a<br>n/a         |
| Cisco            | 9372PX           | 1  | 22.5"  | front<br>rear | rear<br>front | n/a<br>SA1-01002 S | n/a<br>n/a         |
| Cisco            | 9372TX           | 1  | 22.5"  | front<br>rear | rear<br>front | n/a<br>SA1-01002 S | n/a<br>n/a         |
| Cisco            | 9396PX           | 2  | 22.5"  | front<br>rear | rear<br>front | n/a<br>SA1-02003 S | n/a<br>n/a         |
| Cisco            | 9396TX           | 2  | 22.5"  | front<br>rear | rear<br>front | n/a<br>SA1-02003 S | n/a<br>n/a         |
| Cisco ASA        | 5510             | 1  |        | front         | rear          | n/a                | SA2-004            |
| Cisco ASA        | 5540             | 1  |        | front         | rear          | n/a                | SA2-004            |
| Cisco ASA        | 5550             | 1  |        | front         | rear          | n/a                | SA2-004            |
| Cisco ASA        | 5555             | 1  | 19.1"  | front         | rear          | n/a                | SA2-004            |
| Cisco C          | 2620             | 1  |        | side          | rear          | SA1-01001NB        | SA2-003            |
| Cisco Force10    | S50              | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Cisco ME         | 4924             | 1  |        | side          | rear          | SA1-01001NB        | SA2-002            |
| Cisco ASR        | 1001-X-AES-AX    | 1  | 18.5"  | front         | rear          | n/a                | SA2-004            |
| Cisco ASR        | 9001             | 2  |        | side          | side          | n/a                | SA2-003            |
| Cisco ASR        | 9006             | 10 |        | side          | rear          | n/a                | SA2-006            |
| Cisco ISR        | 4431-AX/K9       | 1  | 19.97" | front         | rear          | n/a                | SA2-004            |
| Cisco MCU        | 4501             | 2  | 19.25" | side          | side          | n/a                | SA2-003            |
| Cisco MDS        | 9148             | 1  |        | rear          | front         | SA1-01002          | SA2-002            |
| Cisco MDS        | 9513             | 14 |        | side          | side          | n/a                | SA2-006            |
| Cisco Nexus      | 2148             | 1  |        | rear          | front         | SA1-01002          | SA2-002            |
| Cisco Nexus      | N2k-C2148T-1GE   | 1  | 20"    | rear          | front         | SA1-01002          | SA2-002            |
| Cisco Nexus      | N2K-C2232PP-10GE | 1  | 17.7"  | rear          | front         | SA1-01002          | SA2-002            |
| Cisco Nexus      | 2248             | 1  |        | rear          | front         | SA1-01002          | SA2-002            |
| Cisco Nexus      | N2K-C2248TP      | 1  | 17.7"  | front<br>rear | rear<br>front | n/a<br>SA1-01002   | SA2-004<br>SA2-002 |
| Cisco Nexus      | N7K-C7009        | 14 | 24"    | side          | side          | SA1-09001          | SA2-006            |
| Cisco Nexus      | 2000 series      | 1  |        | rear          | front         | SA1-01002          | SA2-003            |
| Cisco Nexus      | 3048             | 1  | 19.7"  | front<br>rear | rear<br>front | n/a<br>SA1-01002   | SA2-004<br>n/a     |
| Cisco Nexus      | 5672UP           | 1  | 30"    | rear          | front         | n/a                | n/a                |
| Cisco Nexus      | 5672UP           | 1  | 30"    | front         | rear          | n/a                | SA2-004            |
| Cisco Nexus      | 9396             | 2  | 22.5"  | front<br>rear | rear<br>front | n/a<br>SA1-02003S  | n/a<br>n/a         |
| Cisco SGE        | 2010P            | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Cisco SGE        | 2010P            | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | N4032F           | 1  | 18.11" | front         | rear          | n/a                | SA2-004            |
| Dell             | N4064            | 1  |        | front         | rear          | n/a                | SA2-004            |
| Dell             | S4810            | 1  | 18.11" | front<br>rear | rear<br>front | n/a<br>SA1-01002   | SA2-004<br>n/a     |
| Dell             | S4820T           | 1  | 18.11" | front<br>rear | rear<br>front | n/a<br>SA1-01002   | SA2-004<br>n/a     |
| Dell             | 5524             | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | 5548             | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | 5548             | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | S6000            | 1  | 18.11" | front         | rear          | n/a                | SA2-004            |
| Dell             | S6000            | 1  | 18.11" | rear          | front         | SA1-01002          | SA2-002            |
| Dell             | 6224             | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | 6248             | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | 7024             | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | 7048 series      | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Dell             | 8024 series      | 1  |        | front         | rear          | n/a                | SA2-004            |
| Dell             | 8132             | 1  |        | front         | rear          | n/a                | SA2-004            |
| Dell             | 8132F            | 1  |        | front         | rear          | n/a                | SA2-004            |
| Dell             | 8164             | 1  |        | front         | rear          | n/a                | SA2-004            |
| Dell             | 8164F            | 1  |        | front         | rear          | n/a                | SA2-004            |
| Extreme Networks | Summit X430      | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| Extreme Networks | Summit X670V-48x | 1  | 19.25" | front<br>rear | rear<br>front | n/a<br>SA1-01002   | SA2-004<br>n/a     |
| Fortinet         | Fortigate 800C   | 1  |        | sides         | rear          | SA1-01001NB        | SA2-002            |
| F5               | F5-1500          | 1  |        | R-side        | L-side        | SA1-01001NB        | SA2-003            |
| F5               | F5-1600          | 1  |        | front         | rear          | n/a                | SA2-004            |
| NHP ProCurve     | 2824             | 1  |        | L-R sides     | rear          | SA1-01001NB        | SA2-002            |
| HP ProCurve      | 2900-48G         | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |
| HP ProCurve      | 2910AI-48G       | 1  |        | side          | side          | SA1-01001NB        | SA2-003            |

|                    |                      |   |        |               |               |                      |                    |
|--------------------|----------------------|---|--------|---------------|---------------|----------------------|--------------------|
| HP                 | 2920 series          | 1 | 13.23" | side          | side          | SA1-01001NB          | SA2-003            |
| HP                 | 5130 JG937A          | 1 | 14.2"  | side          | side          | SA1-01001NB          | SA2-003            |
| HP                 | 5406ZL               | 4 |        | side          | side          | n/a                  | SA2-006            |
| HP                 | 5412ZL               | 7 |        | side          | side          | n/a                  | SA2-006            |
| HP                 | 5500 EI              | 1 |        | L-side        | R-side        | SA1-01001NB          | SA2-003            |
| HP                 | 5500 JG312A          | 1 | 16.5"  | side          | side          | SA1-01001NB          | SA2-003            |
| HP                 | 5500 SI              | 1 |        | L-side        | R-side        | SA1-01001NB          | SA2-003            |
| HP                 | 5500-48G-4SFP-HI     | 1 | 16.5"  | L-side        | R-side        | SA1-01001NB          | SA2-003            |
| HP                 | 5700                 | 1 | 18.1"  | rear          | front         | SA1-01002            | SA2-002            |
| HP                 | 5800 JC103A          | 1 | 16.81" | side          | side          | SA1-01001NB          | SA2-003            |
| HP                 | 5900                 | 1 | 17.75" | rear          | front         | SA1-01002L           | SA2-002            |
| HP                 | DL360 G6             | 1 |        | front         | rear          | n/a                  | SA2-004            |
| Juniper            | EX2200-C-12T non POE | 1 |        | top -sides    | rear          | SA1-01001NB          | SA2-002            |
| Juniper            | EX2200-C-12P POE     | 1 |        | na            | na            | n/a                  | na                 |
| Juniper            | EX2200-24T           | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| Juniper            | EX2200-24P           | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| Juniper            | EX2200-24T-DC        | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| Juniper            | EX2200-48T           | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| Juniper            | EX2200-48P           | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| Juniper            | EX3300               | 1 | 12"    | front<br>rear | rear<br>front | n/a<br>SA1-01002XLNB | SA2-004<br>SA2-002 |
| Juniper            | J6350                | 2 | 21.13" | front         | rear          | n/a                  | SA2-004            |
| Juniper            | MAG6610              | 1 | 27.25" | front         | rear          | n/a                  | SA2-004            |
| Juniper            | MX480                | 8 |        | side          | side          | SA1-09001            | SA2-006            |
| Juniper            | NS5200               | 2 |        | side          | side          | SA1-02005            | SA2-003            |
| Juniper            | QFX5100-48T-AFI      | 1 | 20.48" | front<br>rear | rear<br>front | n/a<br>SA1-01002     | n/a<br>n/a         |
| Juniper            | SA4000               | 1 |        | side          | rear          | SA1-01001NB          | SA2-003            |
| Juniper            | EX4200               | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| Juniper            | EX4550               | 1 | 18.5"  | rear          | front         | SA1-01002            | SA2-002            |
| Juniper            | SRX240               | 1 |        | side          | side          | SA1-01001NB          | SA2-003            |
| Juniper            | SRX550               | 2 | 18.2"  | side          | side          | SA1-02005            | SA2-003            |
| Juniper            | SRX650               | 2 | 18.2"  | l-side        | r-side        | SA1-02005            | SA2-003            |
| Juniper            | SRX1400              | 3 | 13.8"  | l-side        | r-side        | SA1-03001            | try SA2-006        |
| Juniper            | SRX3600              | 5 | 25.5"  | side          | side          | n/a                  | SA2-006            |
| Juniper            | SRX5400              | 5 | 24.5"  | r-side        | l-side        | n/a                  | SA2-006            |
| Juniper            | SSG320M              | 1 | 15.1"  | side          | side          | SA1-01001NB          | SA2-003            |
| Juniper            | SSG550M              | 2 |        | front         | rear          | n/a                  | SA2-004            |
| Juniper            | WLC2800              | 2 |        | sides         | rear          | n/a                  | SA2-002            |
| Mellanox           | SX-6036G             | 1 |        | rear          | front         | n/a                  | n/a                |
| NetGear            | GSM 7224S            | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| NetGear            | XSM 7224S            |   |        | front         | rear          | n/a                  | SA2-004            |
| NetGear            | GS7252TXS            | 1 | 10.1"  | side          | side          | SA1-01001NB          | SA2-003            |
| NetGear            | GSM 7252S (M5300)    | 1 |        | sides         | rear          | SA1-01001NB          | SA2-002            |
| Palo Alto Networks | M100                 | 1 |        | front         | rear          | n/a                  | SA2-004            |
| Palo Alto Networks | PA3020               | 1 | 17"    | side          | side          | SA1-01001NB          | SA2-003            |
| Palo Alto Networks | PA 5060              | 2 | 21"    | side          | side          | SA1-02005            | SA2-003            |
| SMC                | SMCGS18C-Smart       | 1 | 11"    | side          | side          | SA1-01001MB          | SA2-003            |
| Sonic              | NSA 3500             | 1 |        | side          | rear          | SA1-01001NB          | SA2-002            |
| Watchguard-Firebox | M440                 | 1 | 15"    | front         | rear          | n/a                  | SA2-004            |
|                    |                      |   |        |               |               |                      |                    |